

# **G450/02 - Diablo Controls Loop Detector (DSP-6LP) \*AS A SAFETY DEVICE\***

1. Connect **NO (RELAY)** on the loop detector to the terminal **SHADOW**.
2. Connect **COM (RELAY)** on the loop detector to one of the **COM** terminals.
3. Connect **COM (POWER)** on the loop detector to one of the **COM** terminals.
4. Connect **PWR (POWER)** on the loop detector to terminal **VB**.
5. Connect your buried loop to the two **LOOP** terminals on the loop detector.

Terminal **NC** is not used.

# **G450/02 - Diablo Controls Loop Detector (DSP-6LP) \*AS AN OPENING DEVICE\***

1. Connect **NO (RELAY)** on the loop detector to terminal **EXIT**.
2. Connect **COM (RELAY)** on the loop detector to one of the **COM** terminals.
3. Connect **COM (POWER)** on the loop detector to one of the **COM** terminals.
4. Connect **PWR (POWER)** on the loop detector to terminal **VB**.
5. Connect your buried loop to the two **LOOP** terminals on the loop detector.

Terminal **NC** is not used.