

E-SU2200/02 - GateCrafters Universal Keypad & Proximity Card Reader (PRX-320)

1. Connect **GREEN** wire on the **6-PIN** connector from the keypad to **Terminal OPEN A** on the terminal block CN4.
2. Connect **PURPLE** wire on the **6-PIN** connector from the keypad to **Terminal COM** on the terminal block CN4.
3. Connect **RED** wire on the **6-PIN** connector from the keypad to **POSITIVE** of an external transformer (not included) **12V DC 500-800 mA**.
4. Connect **BROWN** wire on the **6-PIN** connector from the keypad to **POSITIVE** of an external transformer (not included) **12V DC 500-800 mA**.

The 8-PIN and 2-PIN connectors are used for advanced installations, mostly used in commercial settings and are not necessary for the regular usage of this unit.