

# **APOLLO 3500/3600 - Linear Access 2 Channel Digital Keypad (AK-1)**

1. Connect **N.O. 1** on the J3 terminal strip from the keypad to **Terminal INP** on one of the 3 pin terminal strips.
2. Connect **COMMON 2** on the J3 terminal strip from the keypad to **Terminal GND** on one of the 3 pin terminal strips.
3. Connect **+ power1** on the J4 terminal strip from the keypad to **Terminal 12V** on one of the 3 pin terminal strips.
4. Connect **- power 2** on the J4 terminal strip from the keypad to **Terminal GND** on one of the 3 pin terminal strips.